

TJ130JD5S

Diesel Generator Sets / 50 Hz

Power Output Ratings		50 Hz / 400 V
Standby Power (ESP)	kVA	130
Standby Fower (ESF)	kW	104
Prime Power (PRP)	kVA	110
	kW	88

Engine				
Manufacturer			JOHN DEERE	
Origin			FRANCE	
Model			6068TF258	
No of Cylinder / Configuration			6 - INLINE	
Displacement		lt	6,8	
Bore / Stroke		mm	106 / 127	
Compression Ratio			17,0:1	
Aspiration			Turbocharged	
Governor Type			MECHANIC	
Cooling System			WATER	
Coolant Capacity		lt	TBA	
Lubrication Oil Capacity		lt	17	
Electrical System		VDC	12	
Speed / Frequency			1500 rpm / 50 Hz	
Engine Gross Power		kWm	121	
	lt/h —	110 %	29,6	
Fuel Consumption		100 %	26,6	
r der consumption		75 %	22,2	
		50 %	15,1	
Exhaust Outlet Temperature		°C	584	
Exhaust Gas Flow		m³/min	18,6	
Combustion Air Flow		m³/min	7	
Cooling Air Flow		m³/min	TBA	

Origin IND Model UCI22 No of Phase 3 Power Factor 0,4 No of Bearing SING No of Poles 4 No of Leads 12 Voltage Regulation (Steady State) ± %	Alternator						
Model UCI23 No of Phase 3 Power Factor 0,8 No of Bearing SING No of Poles 4 No of Leads 12 Voltage Regulation (Steady State) ± %	STAMFORD						
No of Phase 3 Power Factor 0,8 No of Bearing SING No of Poles 4 No of Leads 12 Voltage Regulation (Steady State) ± %	INDIA						
Power Factor 0,3 No of Bearing SING No of Poles 4 No of Leads 12 Voltage Regulation (Steady State) ± %	UCI274D						
No of Bearing SING No of Poles 4 No of Leads 12 Voltage Regulation (Steady State) ± %	3						
No of Poles 4 No of Leads 12 Voltage Regulation (Steady State) ± %	0,8						
No of Leads 12 Voltage Regulation (Steady State) ± %	SINGLE						
Voltage Regulation (Steady State) ± %							
	12						
Insulation Class	± %1						
	Н						
Degree of Protection IP 2	IP 23						
Excitation System AVR (Automatic Voltage	AVR (Automatic Voltage Regulator), Brushless						
Connection Type STA	STAR						
Total Harmonic Content (No Load) < %	2						
Frequency Hz 50	50						
Voltage Output VAC 230 /	230 / 400						
Rated Power (Standby) kVA 130	130						
Efficiency % 90,	90,2						

	W x L x H (mm)	Weight (kg)	Fuel Tank (It)	Noise dB(A)
Canopied	1037 x 3265 x 1700	TBA	168	TBA
Open Skid	750 x 2400 x 1420	TBA	144	TBA






Standby Power

Standby power is defined as the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 500 hours of operation per year under average of 70% load. Overloading is not permissible.

Prime Power

Prime power is defined as being the maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hours.



- Technical information and values are according to ISO8528, ISO3046,NEMA MG-1.22, IEC 60034-1, BS 4999-5000, VDE 0530 standards. Producing with ISO9001, ISO14001, OHSAS18001, TSE, CE standards.

TBA: To Be Ask

- All information given in this leaflet is intended for general purposes only. Due to a policy continuous improvement Teksan reserves the right to amend details and specifications without notice and all information given is subject to the Teksan's current condition of sales.

TBD: To Be Determined **NA:** Not Avaliable www.teksangenerator.com

TTD130JD5S0612-EN N/A: Not Applicable

